

SAFETY WARNINGS

IMPORTANT SAFETY INFORMATION

14042300 REV C



Before you begin.

Read these instructions completely & carefully.



WARNING Risk of electrical shock. Disconnect power before servicing or installing luminaire. *Avertissement - Risque de choc électrique. Coupez l'alimentation avant l'entretien ou l'installation du luminaire.*




WARNING Risk of injury or damage. Luminaire will fall if not installed properly. Follow installation instructions, NEC and local codes and best trade knowledge. *Avertissement - Risque de blessure ou de dommage. Le luminaire tombera si installé incorrectement. Suivez les instructions d'installation, le NEC, les codes locaux et le meilleur de vos connaissances du métier.*



WARNING Risk of injury. Wear safety glasses and gloves during installation and servicing. *Avertissement - Risque de blessure. Porter des lunettes de sécurité et des gants lors de l'installation et l'entretien.*


Follow information on label & instructions regarding installation near combustible materials, insulation, and building materials & in Dry or Wet locations. Do not install in areas exposed to combustible vapors or gases. **This product must be installed by a person familiar with construction and operation of the product and the hazards involved, in accordance with the applicable installation. Be sure to ground product to avoid potential electrical shock or other potential hazard.** Use of accessory equipment not recommended by the manufacturer or installed inconsistent with instructions may cause an unsafe condition. Do not completely or partially block light emerging from product, as this could cause an unsafe condition. Do not allow other items to come into contact with the product, as this may cause an unsafe condition. **WARNING:** This product may contain chemicals known to the State of California to cause cancer, birth defects and/or other reproductive harm. Thoroughly wash your hands after installing, servicing, handling, cleaning, or otherwise touching this product. This device complies with FCC CFR Title 47 Part 15, Class A requirements for EMI/RFI.

INSTALLATION



Step 1: Inspect Product:


Inspect the product upon receipt and notify the delivery carrier of any damage that may have occurred during shipment. Confirm the product ordered matches the product received by comparing the catalog number listed on the packing slip to the carton label.



Step 2: Open Luminaire:

Remove four (4) front panel mounting screws (A). Remove front panel/lens and set aside in a protected location. Remove and discard packing materials behind the front panel.

Remove three (3) screws (B) holding the j-box cover/LED driver panel and pull it away from the j-box. Throughout the installation process, provide support for the LED driver to **prevent wire abrasion and to avoid stress on the electrical connections.**




Step 3: Prepare for Mounting:

Use punch to remove one or more knockouts (C) as needed for wiring access. Use a Unibit or file if needed to clean off any rough edges. When removing material **avoid excessive shock and keep all debris away from electronic components.**

Use a punch to remove material from desired mounting holes (D). When removing material **avoid excessive shock.**

Remove backing from j-box gasket provided. Position and adhere over mounting surface.




Step 4: Install Product:

Route power conductors through selected access hole(s) and secure conduit fittings (by others) where applicable.

Use mounting holes to securely mount to 4" j-box or directly to dedicated mounting plate where provided.


Connect Line (black), Neutral (white) and Ground (green) connections and insulate to 600VAC.



Reposition j-box cover/LED driver panel and secure with three (3) screws (B). Be sure to **avoid wire abrasion and stress on electrical connections** throughout this process.

Step 5: Close Luminaire:

Make sure the environmental gasket is properly seated in the gasket groove, then reposition front panel/lens and secure with four (4) mounting screws (A). Make sure gasket is slightly compressed, but **do not over tighten** the front panel mounting screws.



Step 6: Turn on Electrical Power:

Confirm proper operation. If luminaire is equipped with a button photocell the front panel/lens may need to be temporarily covered to perform this step.